



FW168 midbass driver

#### FEATIRES

- Die cast chassis
- Hard aluminum cone
- Aluminum phase plug
- 36mm voice Coil
- Low distortion, fast transient

Specifications		Magnet System	
Overall Dimensions	D168X79.5mm	Magnet system type	ferrite
Net. Weight	1.76kgs	Magnetic Gap Height	5.8mm
Nominal Power Handlng	50 W rms	B Flux Density	1.0T
Nominal Impedance	8 Ohms	Bl Product	8.2Tm
Sensitivity 1W/1M	87.3dB	Max Linear Excursion	4.6mm +/-
Frequency Response	40-4,000Hz	T/S Parameter	
Resonant frequency	45Hz	Cms	0.821mm/N
Voice Coil		Sd	119cm <sup>2</sup>
Voice Coil Diameter	36mm	Vas	16.5L
Voice Coil Height	15mm	Mmd	13.955gm
Voice Coil Former	Black aluminum	Mms	14.7gm
Voice Coil Wire	copper round	Qms	3.246
Number of Layers	2	Qes	0.452
DC Resistance	7.2 Ohms	Qts	0.397

## SPL vs Freq

